



EXH

Two-Way Radio Antenna

FEATURES

- Injection molded $\frac{1}{4}$ wave base loaded antenna
- High gain
- High durability, high efficiency
- Textured finish with strain-relief base
- Available in various standard connectors
- An original 'Tuf Duck' antenna

PARAMETER	SPECIFICATION
Frequency Range	VHF
Nominal Impedance	50 ohms
VSWR	2:1 max at resonance
Power Rating	Max Power - 50 watts
Temperature Range	-40°C to +85°C
Drop Test	1M
Length ¹	10.50 inches

¹ The length noted is the maximum possible length for this LMR antenna. The actual length of the antenna will vary according to the connector chosen.

FREQUENCIES AND CONNECTOR

PART#	FREQUENCY BAND	CONNECTORS	COLOR CODE
EXH150	145-155 MHz	BN, KR, MX, SF, SFU, SM, SMV & TN	Red
EXH155	150-160 MHz	BN, KR, MD, MX, SF, SFU, SM, SMV & TN	Brown
EXH160	155-165 MHz	BN, KR, MX, SF, SFU, SM, SMV & TN	Black
EXH170	165-175 MHz	BN, KR, MD, MX, SF, SFU, SM, SMV & TN	Orange

The EXH model antenna is available in the above frequencies and connectors. Order by antenna model, frequency and connector.
For example: EXH150SF. Specifications subject to change without notice.

TE TECHNICAL SUPPORT CENTER

USA:	+1 (800) 522-6752
Canada:	+1 (905) 475-6222
Mexico:	+52 (0) 55-1106-0800
Latin/S. America:	+54 (0) 11-4733-2200
Germany:	+49 (0) 6251-133-1999
UK:	+44 (0) 800-267666
France:	+33 (0) 1-3420-8686
Netherlands:	+31 (0) 73-6246-999
China:	+86 (0) 400-820-6015

te.com

TE, TE Connectivity, TE connectivity (logo), and EVERY CONNECTION COUNTS are trademarks owned or licensed by the TE Connectivity plc family of companies. Other product names, logos, and company names mentioned herein may be trademarks of their respective owners.

While TE has made every reasonable effort to ensure the accuracy of the information in this document, TE does not guarantee that it is error-free, nor does TE make any other representation, warranty or guarantee that the information is accurate, complete, correct, reliable or current. TE reserves the right to make any adjustments to the information contained herein at any time without notice. TE EXPRESSLY DISCLAIMS ALL IMPLIED WARRANTIES REGARDING THE INFORMATION CONTAINED HEREIN, INCLUDING, BUT NOT LIMITED TO, ANY IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. In no event will TE be liable for any direct, indirect, incidental, special or consequential damages arising from or related to recipient's use of the information. It is the sole responsibility of recipient of this information to verify the results of this information using their engineering and product environment. Recipient assumes any and all risks associated with the use of the information. Antenna performance may vary. TE is a component manufacturer, and customer and/or end-user is responsible for all end-use compliance and regulatory requirements.

©2025 TE Connectivity. All Rights Reserved.
05/25 Original

